

Accessory for strips 3NJ41 In-line fuse switch disconnectors Sz. NH00 Current transformers can be integrated 100/1 A, Cl. 1



Figure similar

Model	
product brand name	SETRON
product designation	Current transformer
design of the product	accessory for fuse switch disconnector 3NJ41
operating voltage	0.72 kV
insulation voltage rated value	3 kV
designation of overcurrent limiting factor	FS 5
current	
• at input rated value	100 A
value range of the operating frequency	50/60 Hz
Protection class	
protection class IP	IP20
Mechanical Design	
height	60 mm
width	46 mm
depth	19 mm
net weight	241 g
Environmental conditions	
ambient temperature during operation	
• minimum	-10 °C
• maximum	55 °C
Approvals Certificates	
General Product Approval	other

[Confirmation](#)



[Confirmation](#)

[Miscellaneous](#)

Environment

[Environmental Con-
firmations](#)

Further information

Information on the packaging
<https://support.industry.siemens.com/cs/ww/en/view/109813875>

Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/lowvoltage/catalogs>

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3NJ4915-1EA20>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3NJ4915-1EA20>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3NJ4915-1EA20

CAX-Online-Generator

<http://www.siemens.com/cax>

Tender specifications

<http://www.siemens.com/specifications>

last modified:

5/24/2024 

