

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

PRODUCT DATASHEET

ST 111 LONGLIFE

Starters for single operation at 230 V AC (ST 111, ST 171, ST 173) | Starters for single operation at 230 V AC



Product features

- Temperature range for reliable cut-out: -20...+80 °C

choose one

Country

[myLEDVANCE](#)

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

TECHNICAL DATA

Electrical data

Nominal wattage	65.00 W
Nominal voltage	220...240 V
Mains frequency	50/60 Hz

Dimensions & Weight

Diameter	21,5 mm
Product weight	6.58 g

Additional product data

Mercury content	0.0 mg
Product remark	Not suitable for L 70 W / Starters are available in two different designs, with identical technical features

Capabilities

Dimmable	No
----------	----

Country-specific categorizations

Order reference	ST 111
-----------------	--------

Energy labelling regulation data acc EU 2019/2015

Length	40.30 mm
Height	21,5 mm
Width	21.50 mm

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4050300064000	Blister 2	140 mm x 24 mm x 105 mm	34.09 g	0.35 dm ³
4050300119588	Shipping box 20	165 mm x 154 mm x 150 mm	321.27 g	3.81 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

Oops! An Error Occurred

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.