

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

FICHA TÉCNICA DEL PRODUCTO ST 151 LONGLIFE

Starters for series operation at 230 V AC (ST 151, ST 172) | Cebador para conexión en serie en 230 V AC



Características del producto

- Margen de temperatura para desconexión segura: -20...+80 °C)

Oops! An Error Occurred

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

INFORMACIÓN TÉCNICA

DATOS ELÉCTRICOS

Potencia nominal	22,00 W
Tensión nominal	220...240 V
Frecuencia de red	50/60 Hz

DIMENSIONES Y PESO

Diámetro	21,5 mm
Peso del producto	6,43 g

DATOS ADICIONALES DEL PRODUCTO

Contenido mercurio	0.0 mg
Pie de pág. usado solo para el producto	Los arrancadores están disponibles en dos diseños diferentes, con idénticas características técnicas

PRESTACIONES

Regulable	No
-----------	----

Categorizaciones específicas de país

Referencia para pedido	ST 151 LONGLIFE
------------------------	-----------------

Datos de regulación de etiquetado energético (EU 2019/2015)

Largo	40,30 mm
Altura (luminarias incluidas)	21,5 mm
Ancho (incl. Luminarias redondas)	21.50 mm

DATOS LOGÍSTICOS

Código de producto	Cantidad por caja (unidad/master)	Dimensiones (longitud x largo x altura)	Peso bruto	Volumen
4050300092638	Blíster 2	111 mm x 24 mm x 68 mm	26.10 g	0.18 dm³
4050300119595	Embalaje de envío 20	165 mm x 154 mm x 133 mm	308.67 g	3.38 dm³

El codigo de producto mencionado describe la cantidad minima de unidades que puede ser comprada. Una unidad de transporte puede contener uno o más productos individuales. Cuando se realiza la compra, para las cantidades porfavor ingrese una o varias unidades de envío.

DESCARGO DE RESPONSABILIDAD

Oops! An Error Occurred

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

Sujeto a cambio sin aviso. Errores y omisiones exceptuadas. Asegurese de utilizar la version más reciente.

Oops! An Error Occurred

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.